



Is Five Greater Than Four? ALWAYS!



CCM5G Series
Five-Tube Changer

More Change. Less Cost.

The Conlux CCM5G Series Five-Tube Coin Changer's bigger bank remains filled longer at your vend prices, so you never lose a sale. It costs less than competitors' smaller models and is built to last the life of your machines—which means no future replacement costs!

Exclusive Features

- **Five Tubes:** More change capacity eliminates possibility of change starvation. Sells more product and eliminates service calls.
- **Front Tube Cassette:** Self recognition by coin changer means no programming needed by service technician, thus no possibility of errors being made in programming.
- **Easy Loading Tube Cassette:** Tubes can be pre-loaded two ways: (1) through the top of the tube or (2) by opening the tube and placing a roll of coins in at one time.
- **Payout System:** Payout three coins simultaneously which increases throughput in high volume locations and reduces motor wear.

CONLUX®

A Change for the Better!


P.O. Drawer 719 11685 Main Street Williston, SC 29853
800-688-9090 • Fax 803-266-5049 • www.dixienarco.com/conlux

CCM5G Series Five-Tube Coin Changer



Specifications

Interface	Multi-Drop Bus (M.D.B.)
Operating Voltage	34 Volt D.C.
Power Consumption	Standby 0.10A
Operating State	Motor Operation 0.66A or less (Peak max. 5 sec. 0.92A)
Operating Temperature Range	5°F (-15°C) to +140°F (+60°C)
Insulation Resistance	20 M Ohm or more
Weight	4.2 lbs. (1.9 Kg.)
Dimensions (HxWxD)	14.83" x 5.43" x 3.23" (376 x 137 x 82mm)
Number of Motors	1 Motor — 15 Volt D.C.
Number of Solenoids	5 for Coin Selection (15 Volt D.C.)
Coin Acceptance	5¢, 10¢, 25¢, \$1, \$2 U.S. Only, Canadian Only, or Both
Maximum Coin Capacity (±3 Coins Each Tube)	US-1 Cassette (1N, 1D, 3Q) = \$82.65 US-2 Cassette (2N, 2D, 1Q) = \$53.10 US-4 Cassette (1N, 1D, 2Q, 1 \$) = \$137.90 US-5 Cassette (2N, 3D) = \$43.10
Optional Satellite Coin Tubes (±3 Coins Each Tube)	ST-5 (110 Nickels)=\$5.50 ST-25 (130 Quarters)=\$32.50



DIS = discriminator
C/C = coin changer

Diagnostics and Control Functions

- Two LED's are provided to indicate coin changer or discriminator malfunctions. LED (DIS) Red indicates discriminator malfunction and LED (C/C) indicates coin changer malfunctions. In operating state, both LEDs are ON. Corresponding LEDs will blink if failure is detected, in either coin changer or discriminator section.
- Use switches A thru E, to inventory coins from the corresponding tubes. The functions "SAT," "MOD" and "AUT" switches are explained in detail in the service manual.

Additional Features

- **Simple Design/ Fewer Parts**
- **M.D.B. Interface**
- **LED Diagnostic**
- **Dollar Coin Payout**
- **Removable Coin Cassette**
- **Acceptance of Up to 12 Different Coins (electronically)**
- **Smart Payout:** Makes sure coin was paid out and if not, will try to pay that coin out one more time, resulting in less service calls.
- **Satellite Payout:** Add more tubes—up to 7 maximum—for greatest change capacity.
- **Last Coin Payout:** No dead inventory.
- **Anti-Salting System:** Unique diversion channel protects changer and vendor from salt water damage and vandalism.
- **Memory Back-Up:** The coin changer will retain its memory in case of power failure.
- **Swing Open Payout Base**
No tools needed to remove base for cleaning.
- **Excellent 3-Year Customer Protection Plan**
- **The Perfect Partner for Our NBM-3000 Series Bill Validator**



P.O. Drawer 719 11685 Main Street Williston, SC 29853
800-688-9090 • Fax 803-266-5049 • www.dixienarco.com/conlux

A Change for the Better!