



KIT PART NUMBER 1570072

INSTRUCTIONS FOR INSTALLING AN MDB SOFTWARE UPGRADE IN A SNACK OR REFRESHMENT CENTER

CHECK THE PARTS RECEIVED IN THE KIT WITH THE PARTS LIST IN THESE INSTRUCTIONS. IF ANY PARTS ARE MISSING, CONTACT THE NATIONAL VENDORS PARTS DEPARTMENT IMMEDIATELY.

Read these instructions carefully before installing the kit.
Keep these instructions for part numbers and for future reference.

This kit contains the following:

INDEX	PART NUMBER	DESCRIPTION	QUANTITY
1	P1586002	IC ASSEMBLY - VERSION 158.02	1
2	1470035	ELECTROSTATIC CAUTION SHEET	1
3	1570005	PROGRAMMING GUIDE - SNACK & REFRESHMENT CENTER	1
4	1570044	SET-UP GUIDE - SNACK CENTER	1
5	1570058	SUPPLEMENT TO 1570044 - SNACK	1
6	1570069	WIRE DIAGRAM SUPPLEMENT - MDB	1
7	6335002	SERVICE KEYPAD ASSEMBLY	1
8	1570073	INSTALLATION INSTRUCTIONS	1

Proceed as follows:

NOTE:
If your service keypad looks like this, make sure you have kit number 1570072. Your new software will not work with this keypad! You will need to replace it with the keypad included in this kit.

1. Turn the main power switch to OFF.
2. Carefully remove the old EPROM from the controller board.
3. Install the new EPROM into the socket exactly as the old one was.

If you do not have the keypad shown on the left, skip to step 7.

4. Disconnect the keypad harness from the display board.
5. Using a flat-bladed tool such as a putty knife, carefully pry the old keypad off the face of the monetary panel.
6. Peel the backing from the new keypad, attach it to the monetary panel, and connect the harness to the display board.
7. Turn the main power switch ON and test operate your machine.
8. If you have a RAM ERR message, refer to the DIAGNOSTIC MESSAGES section of your new programming guide (1570005) for instructions.

DECLINING BALANCE: Once credit is established, multiple vendors may occur until the coin return is received.